





Code: **ICF**

Socket Cap Screw Counterbore




Application Examples



M	d	d1	d2	l	l1	l2
M3	6	3.2	5	71	14	4
M4	8	4.3				
M5	10	5.3	8	80	18	6
M6	11	6.4				
M8	15	8.4	12.5	100	22	8
M10	18	10.5				
M12	20	13	100	22	14	12
M14	24	15				
M16	26	17	100	22	16	16
M18	30	19				
M20	33	20	100	22	18	20
M20	33	20				

Order: **ICF. M x d**

Straight Stud




Order	M	Steel	INOX
GSM.3	M3	✓	
GSM.4	M4	✓	
GSM.5	M5	✓	
GSM.6	M6	✓	✓
GSM.8	M8	✓	✓
GSM.10	M10	✓	✓
GSM.12	M12	✓	✓
GSM.14	M14	✓	✓
GSM.16	M16	✓	✓
GSM.18	M18	✓	
GSM.20	M20	✓	
GSM.22	M22	✓	
GSM.24	M24	✓	



Order / Code: **HIC. d x L**

Countersunk Head Screw
Class: 10.9 DIN 7991




Code: **HIC**

d	l _{mm}	l1	D	k	s
M3 x 05	8	3.2	6	1.7	2
	10				
	15				
M4 x 07	10	4.4	8	2.3	2.5
	15				
	20				
	25				
	30				
M5 x 08	10	5.2	10	2.8	3
	15				
	20				
	25				
	30				
	35				
	40				
M6 x 1	10	6.3	12	3.3	4
	15				
	20				
	25				
	30				
	35				
M8 x 1.25	10	8.2	16	4.4	5
	15				
	20				
	25				
	30				
	35				
M10 x 1.50	15	10	20	5.5	6
	20				
	25				
	30				
	35				
	40				
	50				
M12 x 1.75	20	11.8	24	6.5	8
	25				
	30				
	35				
	40				
	50				
	60				
M16 x 2	25	15.4	30	8.5	10
	30				
	35				
	40				
	50				
	60				
	70				



Order / Code: **SEC. d x L**

Hex-socket Set Screws




Code: **SEC**

d	l _{mm}	Z	SW
M3 x 05	8	0.5	1.5
	10		
	15		
M4 x 07	8	0.7	2
	10		
	15		
M5 x 08	10	0.75	2.5
	15		
	20		
	25		
	30		
M6 x 1	10	1.0	3.0
	15		
	20		
	25		
	30		
	35		
	40		
M8 x 1.25	10	1.2	4.0
	15		
	20		
	25		
	30		
	35		
	40		
M10 x 1.50	10	1.5	5.0
	15		
	20		
	25		
	30		
	35		
	40		
M12 x 1.75	10	2.0	6.0
	15		
	20		
	25		
	30		
	35		
	40		
M14 x 2	20	2	7
	25		
	30		
	35		
	40		
	50		
	60		
M16 x 2	20	2	8
	25		
	30		
	35		
	40		
	50		
	60		



Order / Code: **DKM. d1 x L**

Low Head Socket Cap Screw
Class: 8.8 DIN 79849



Code: **DKM**

d1	l _{mm}	b	d2	k	s
M4	10	8	7	2.8	2.5
	12	10			
	16	14			
	20	14			
M5	10	8	8,5	3,5	3
	12	10			
	16	14			
	20	16			
	25	16			
	30	16			
	35	16			
M6	10	8	10	4	4
	12	10			
	16	14			
	20	18			
	25	18			
	30	18			
	35	18			
M8	16	14	13	5	5
	20	18			
	25	22			
	30	22			
	35	22			
	40	22			
	50	22			
M10	16	14	16	6	7
	20	18			
	25	22			
	30	26			
	35	26			
	40	26			
	50	26			
M12	20	18	18	7	8
	25	23			
	30	28			
	35	30			
	40	30			
	50	30			
	60	30			